

XLE – Edge Lit Exit Sign

👁️ XLE Basics

- Dual Voltage 120/277
- Order Single or Double Faced
- Order in Red or Green
- 90 Minute NiCad Battery
- Long Life, 1.2 Watt Red or 1.5 Watt Green, LED Light Source

👁️ Mounting Details

- Surface mount version comes with a canopy that allows it to be ceiling, end or wall surface mounted.
- Recessed version also available.

👁️ Battery Details

- Maintenance free, Sealed Nickel Cadmium battery provides a minimum 1½ hour emergency operation for Self-Powered signs.
- Low voltage disconnect of the battery prevents deep discharge and maintains good battery life.
- Fully automatic, solid state charger.
- Test switch with LED charge indicator/AC voltage indicator.

👁️ Why P2 for LED Exits?

- Always in Stock for Quick Ship
- Complete your relighting project bill of materials, kits, fixtures, indoor, outdoor, exits, with a single PO.


👁️ Approvals

- UL924
- Life Safety NFPA 101
- UL Listed for Damp Location


👁️ XLE – Edge Lit Exit Sign with Battery Backup



Surface Mount



Recessed Mount



Ordering Information

- XLE-R-S = Single Face, Red Letter, Universal Volt, Edge Lit LED Exit with Battery Backup
- XLE-R-D = Double Face, Red Letter, Universal Volt, Edge Lit LED Exit with Battery Backup
- XLE-G-S = Single Face, Green Letter, Universal Volt, Edge Lit LED Exit with Battery Backup
- XLE-G-D = Double Face, Green Letter, Universal Volt, Edge Lit LED Exit with Battery Backup

Note

Add -REC for Recessed Mount Version